

## TXM-0508

Universal GSM/GPRS Dialer



GSM/GPRS dialer is used to deliver alarm information from intruder alarm panels or fire alarm panels to the users over GSM by voice call and SMS and can connect directly with the Alarm Receiving Centers to deliver alarm information via GPRS. It can also be used to remote start/stop of a product connected over PGM output via SMS. It can be used with all brand of fire alarm panels.

**SUPPORT ALL SYSTEMS WITH RELAY OUTPUT WITH ANY BRAND OF ALARM AND FIRE PANELS**

### GENERAL FEATURES

- 15 Seconds Sound Recording
- GPRS Connection with ARC
- 2X Zone Inputs (Fire and Error)
- 1X PGM Output
- 8X Call and 8X SMS for Each Zone
- SMS Notification when Fault on ARC Connection or Fault on Control Panel Connection
- LEDs indicating Operation, Communication and Signal statuses

TXM-0508 Module can be program via TXM Configuration software.

### Technical Specifications

### TXM-0508

Power	10-24 VDC 300mA
Standby Consumption	500mA
Alarm Consumption	120mA
GSM Modem Frequency	850/900/1800/1900 Mhz
Sound Recording Time	15sec
Communication Format	SIA-DC-09
Zone Inputs	2 (NC/NO)
Outputs (PGM)	1
Number of Users Call	8x Per Each Zone
Number of Users SMS	8x Per Each Zone
SMS Character	50
Dimensions (mm)	150 x 110 x 35 mm
Operating Temperature	-20...+55°C
Humidity	95% RH

PSTN'Panel

Universal Gsm  
Dialer

Users